








## RGB+CCT LED Downlight Model No.:LM070-LM072

-  RGB+CCT  
16 Millions of colors to choose
-  Color temperature  
2700~6500K
-  Dimmable  
Saturation control
-  2.4G RF wireless transmission  
technology
-  Signal transmitting &  
Modes synchronization
-  Remote control  
Control distance 30m
-  Smart phone APP control  
(2.4GHz gateway is needed)
-  Support third party voice control  
(2.4GHz gateway is needed)

## 12W RGB+CCT LED Downlight Model No.:LM072

Input Voltage: AC100~240V 50/60Hz  
Power: 12W  
Working Temp.: -20~60°C  
CRI: >80 PF: >0.5  
Color Temperature: 2700K~6500K  
Luminous Flux: 1100LM  
Light Efficiency: 88LM/W  
Lifespan: 50000 hours  
Beam Angle: 120°  
RF: 2.4GHz  
Transmitting Power: 6dBm  
Control Distance: 30m  
Material: ALuminum+PC Cover  
Product Weight: 320g




Hole Size:  $\phi$ 145~150mm

## 1. Features

## 6W RGB+CCT LED Downlight

Model No.:LM070

Input Voltage: AC100~240V 50/60Hz  
Power: 6W  
Working Temp.: -20~60°C  
CRI: >80 PF: >0.5  
Color Temperature: 2700K~6500K  
Luminous Flux: 600LM  
Light Efficiency: 85LM/W  
Lifespan: 50000 hours  
Beam Angle: 120°  
RF: 2.4GHz  
Transmitting Power: 6dBm  
Control Distance: 30m  
Material: ALuminum+PC Cover  
Product Weight: 160g




Hole Size:  $\phi$ 90~95mm

## 9W RGB+CCT LED Downlight

Model No.:LM071


Input Voltage: AC100~240V 50/60Hz  
Power: 9W  
Working Temp.: -20~60°C  
CRI: >80 PF: >0.5  
Color Temperature: 2700K~6500K  
Luminous Flux: 720LM  
Light Efficiency: 80LM/W  
Lifespan: 50000 hours  
Beam Angle: 120°  
RF: 2.4GHz  
Transmitting Power: 6dBm  
Control Distance: 30m  
Material: ALuminum+PC Cover  
Product Weight: 200g



Hole Size:  $\phi$ 110~125mm


## Instructions

1. Please open the hole on the ceiling according of Diagram 1. ( For the size of the hole, please refer to the parameters of the corresponding model. )
2. Connect the driver properly according to the wire connection Diagram 2. And then put the driver and wire into the ceiling from the hole.
3. Push in the two spring elements, make sure that they are deployed and anchored on the back of the ceiling Diagram 3 and 4.



## Link/Unlink

Compatible with these remote controls  
(Purchased separately)



**NOTE:**  
Lighting can be working after linking with remote;  
for more details, pls read the remote instruction.

## Dynamic Mode Sheet


No.:	Dynamic Mode	"Brightness / Saturation / Speed"	Auto-Sync
1	Riotous Profusion	Adjustable	Under same remote, same zone, same speed and dynamic mode, lights can be auto-sync
2	Blue Sky		
3	Gorgeous Color		
4	Ocean		
5	Dreamlike		
6	Christmas		
7	Forest		
8	Birthday		
9	Blooming		

## Signal transmitting

One Downlight can transmit the signals from the remote control to another Downlight within 30m, as long as there is a Downlight within 30m, the remote control distance can be limitless.

## Modes synchronization

Different Downlight can work synchronously when they are started at different times, controlled by the same remote, under same dynamic mode and within 30m distance.



## Attention

1. When install the lighting fixtures, pls switch off the power to make sure the safety.
2. Please check whether the input voltage supply is in accordance with the lighting fixtures.
3. Non-professional user cannot dismantle the lighting fixtures directly, otherwise, it may cause fire and electric shock.
4. Please do not use lighting fixtures around the mental area and high magnetic field, otherwise, it will badly affect the control distance.