


T3X

2.4G LED RGB Programmable Controller



T3X is the 2.4GHZ RF wireless synchronization RGB controller which adopts our company multiple global initiate technology. The control system consists of two parts, the RF remote control and receiver, realize the signal synchronization on unlimited receivers within effective distance. a very good solution for the LED project needs sync control wirelessly. User-friendly full-color touch wheel for color selection, unique LED state light for sync change indicated, user can simply know the LED working state from distance by checking the remote control.

Can RF remote the functions of switch, pause, mode, speed and LED brightness, more proudly, the T3X has the brand-new programmable function, only 10 seconds can DIY a new change effect easily. Programming never been so easy!

1. Technical Specs:

T3X Remote Control

- Input Voltage: DC5V Built-in Lithium Battery
- Working Current: <30mA
- Working Frequency: 2.4GHZ
- RF Remote Distance: 30m
- Remote Option: sync control unlimited receivers
- Change mode: 32 Fantastic modes
- Battery Capacity: 1000mAh
- Standby Tme: 6 Months
- Normal Using Time: 30 Days
- Dimension: L145×W55×H22(mm)
- Package Size: L168×W102×H28(mm)
- Weight (G.W.): 200g

T3-5A CV Receiving controller

- Input voltage: DC12V-DC24V
- Max current load: 5A×3CH Max 15A
- Max output power: 180W/360W(12V/24V)
- Control button: 8 touch button
- Compatible remote control: workable with T3, T3M, T3X

- Working temperature: -30℃~55℃
- Dimension: L211×W40×H30mm
- Package size: L215×W42×H32mm
- Weight (G.W.): 180g

T3-CV Receiving controller

- Input voltage: DC5V-DC24V
- Max current load: 5A×3CH Max 15A
- Max output power: 75W/180W/360W(5V/12V/24V)
- Compatible remote control: T1/T2/T2M/T3/T3M/T3X
- Working temperature: -30℃~55℃
- Dimension: L175×W44×H30(mm)
- Package size: L178×W48×H33mm
- Weight (G.W.): 110g


T3-CC Receiving controller (current 3 in 1)

- Input voltage: DC12V-DC48V
- Output voltage: DC3V-DC46V
- Output current: CC 350/700/1050mA ×3CH
- Driving LEDs: 1-13 LEDs in series connection(1W/3W/5W)
- Compatible remote control: T1/T2/T2M/T3/T3M/T3X
- Working temperature: -30℃~55℃
- Dimension: L175×W44×H30(mm)
- Package size: L178×W48×H33mm
- Weight (G.W.): 110g


2. Performance Features:

1. Adopt 2.4GHZ RF wireless transmission technology, which is applicable for license and patent free worldwide.
2. Built-in with dual-core driver, make it 10 times of processing speed. can process the wireless data transmission in complicated and multiple levels.
3. Advanced RF wireless sync control technology, no sync signal wire between receivers, sync capability is stable and reliable.
4. Remote control adopts the capacitive touch control technology on the full color wheel, make the LED color selection more user-friendly.
5. With the unique and creative programming function in the remote control, how easy to program is!
6. Built-in sync state light, can display the LED color in static or changing state synchronously.
7. Any operation on the remote control or any receiver can command all receivers to work wirelessly and synchronously.
8. Color changing scene mode and preset storage function.
9. USB charging port.

3. Product Size:




T3X RF remote control



T3-5A

T3-CV/T3-CC

4. Operation Panel and Component Instruction:



DIY Key for Color Selection


- Long press "DIY key for color selection" for 2 seconds to enter DIY programming function.

1. Select any color on "touch full-color circle", the controller will save immediately.
2. Press "DIY key for color selection" to enter next color.(can save 1-10 colors)
3. After color selection, press "Switch key for changing modes" to switch jumping, smooth or flickering changing effect.
4. Adjust the brightness and the speed by pressing the "SPEED" and "BRT"
5. Save the new program into the "Scene-save keys".

- Additional functions:

- ▲ Long press "DIY key for color selection" to clear the current color.
- ▲ Press "MODE" key under DIY function, can display the standard color for black, red, green, blue, yellow, purple, cyan and white. Among them, black can be used for editing fade in dimming effect, etc.

★Other function: Press "Scene-save Key" ^{PLAY} in 3 seconds, the buzzer can be on or off.



5. The Charging Methods for Remote Control:

1. When charging, please connect USB cable to the mobile charger or computer with the USB interface.
2. The blue indicator light flickers while charging, and turns green means the charging is completed. The remote control can be chargeable even at the OFF state, on which the indicator light is black.
3. No memory effect in the lithium battery of remote control. Follow the standard charging procedure even for the first three times, no need over charge.
4. Red indicator light flickers meaning low battery and need to be charged. charging in low battery will affect life of battery.
5. Please make sure about 50% battery remaining on the remote control for long time no use, and it needs to be charged at least two or three months, otherwise the capacity of the battery would be decreased or the battery gets damaged.

6. The learning ID method of remote control:

Learning ID:

1. Turn on the receiver and remote control.
2. Press "on/off button" on the T3-5A or "ID learning button" on the T3-CV, T3-CC for 2 seconds, there is a buzzer sound, and do not release your hand on the button, at the same time press any keys on the remote control(except on/off key), until the remote control green LED indicator light flashes 3 times(a voice prompt at the same time), release all the keys.

If you have to control many receivers synchronously, each receiver should be learning ID according to the above steps learning ID.

Cancelling ID:


1. Turn on the receiver and remote control.
2. Press "on/off button" on the T3-5A or "ID learning button" on the T3-CV, T3-CC for 2 seconds, there is a buzzer sound, and do not release your hand on the button, after 5 seconds press any keys on the remote control(except on/off key), until the remote control red LED indicator light flashes 3 times(a voice prompt at the same time), release all the keys.

7. Tables of Changing Mode:

No.	Mode	Description	No.	Mode	Description
1	Static Red	Brightness Adjustable	17	Cyan Fade out and Fade in	Speed/Brightness Adjustable
2	Static Green	Brightness Adjustable	18	White Fade out and Fade in	Speed/Brightness Adjustable
3	Static Blue	Brightness Adjustable	19	RGB Fade out and Fade in	Speed/Brightness Adjustable
4	Static Yellow	Brightness Adjustable	20	Red Green Color Smooth	Speed/Brightness Adjustable
5	Static Purple	Brightness Adjustable	21	Red Blue Color Smooth	Speed/Brightness Adjustable
6	Static Cyan	Brightness Adjustable	22	Green Blue Color Smooth	Speed/Brightness Adjustable
7	Static White	Brightness Adjustable	23	Red Yellow Color Smooth	Speed/Brightness Adjustable
8	RGB Skipping	Speed/Brightness Adjustable	24	Green Cyan Color Smooth	Speed/Brightness Adjustable
9	7 Colors Skipping	Speed/Brightness Adjustable	25	Blue Purple Color Smooth	Speed/Brightness Adjustable
10	White Strobe	Speed/Brightness Adjustable	26	Green Yellow Color Smooth	Speed/Brightness Adjustable
11	7 Colors Strobe	Speed/Brightness Adjustable	27	Blue Cyan Color Smooth	Speed/Brightness Adjustable
12	Red Fade out and Fade in	Speed/Brightness Adjustable	28	Red Purple Color Smooth	Speed/Brightness Adjustable
13	Green Fade out and Fade in	Speed/Brightness Adjustable	29	Blue White Color Smooth	Speed/Brightness Adjustable
14	Blue Fade out and Fade in	Speed/Brightness Adjustable	30	Yellow Purple Cyan Color Smooth	Speed/Brightness Adjustable
15	Yellow Fade out and Fade in	Speed/Brightness Adjustable	31	RGB Color Smooth	Speed/Brightness Adjustable
16	Purple Fade out and Fade in	Speed/Brightness Adjustable	32	Full-color Smooth	Speed/Brightness Adjustable


8. System Diagram:

Unlimited receivers can be installed within effective distance, no wiring needed between the receivers, which can be less or more in quantity according to your need for the installation, if you want to increase or decrease the receivers, just activate or cancel the control ID on the remote control will be fine, no any changes and effects on other receivers.




9. Wiring Diagram:

1. Multiple Receivers are Powered by One Power Supply :



5

2. Each Receiver is Powered by One Power Supply Independently :



10. Attention

- The product shall be installed and serviced by a qualified person.
- This product is non-waterproof. Please avoid the sun and rain. When installed outdoors please ensure it is mounted in a water proof enclosure.
- Good heat dissipation will prolong the working life of the controller. Please ensure good ventilation.
- Please check if the output voltage of any LED power supplies used comply with the working voltage of the product.
- Please ensure that adequate sized cable is used from the controller to the LED lights to carry the current. Please also ensure that the cable is secured tightly in the connector to avoid the accidents due to overheat and poor contact on the wire.
- Ensure all wire connections and polarities are correct before applying power to avoid any damages to the LED lights.
- If a fault occurs please return the product to your supplier. Do not attempt to fix this product by yourself.

11. Warranty Agreement

- We provide lifelong technical assistance with this product:
 - A 5-year warranty is given from the date of purchase. The warranty is for free repair or replacement and covers manufacturing faults only.
 - For faults beyond the 5-year warranty we reserve the right to charge for time and parts.
- Warranty exclusions below:
 - Any man-made damages caused from improper operation, or connecting to excess voltage and overloading.
 - The product appears to have excessive physical damage.
 - Damage due to natural disasters and force majeure.
 - Warranty label, fragile label and unique barcode label have been damaged.
 - The product has been replaced by a brand new product.
- Repair or replacement as provided under this warranty is the exclusive remedy to the customer. Ltech shall not be liable for any incidental or consequential damages for breach of any stipulation in this warranty.
- Any amendment or adjustment to this warranty must be approved in writing by Ltech only.

★ This manual only applies to this model. Ltech reserves the right to make changes without prior notice.

6