

60W DALI D4i DT6 NFC LED Driver(Constant Current)



Important: Read All Instructions Prior to Installation

Function introduction



Product Data

Output	LED Channel	1
	DC Voltage	10-54V
	Current	900-1700mA via NFC setting; Min. current gear lower to 0.1mA, Default 1500mA
	Current Accuracy	±3% (±1% @ Certain full load) @ full load
	Rated Power	Max. 60W
Input	Voltage Range	220-240VAC/ 176-280VDC
	Frequency Range	0/50/60Hz
	Power Factor (Typ.)	> 0.98 @ 230VAC Full load
	Total Harmonic Distortion	THD ≤ 5% (@ full load / 230VAC)
	Efficiency (Typ.)	> 87% @ 230VAC full load
	AC Current (Typ.)	0.4A @ 230VAC
	Inrush Current (Typ.)	Max. 25.9A at 230VAC; 148µs duration
	Leakage Current	< 5mA / 230VAC
	Standby Power Consumption	< 0.5W
Control	Anti Surge	L-N:2KV
	Dimming Interface	DALI Device Type 6 (DALI consumption < 2mA)/ AC Push
	Dimming Range	0.01%-100% @ Max current
	Dimming Method	Amplitude/CCR dimming
	Dimming Curve	Linear/ Logarithmic optional

Protection	Short Circuit	Yes, recovers automatically after fault condition is removed
	Over Current	Yes, recovers automatically after fault condition is removed
	Over Temperature	Yes, recovers automatically after temperature drop
Environment	Working Temp.	-25°C ~ +60°C
	Max. Case Temp.	TC=90°C
	Working Humidity	10% ~ 95% RH non-condensing
	Storage Temp. & Humidity	-40°C ~ +80°C, 10% ~ 95% RH
Safety & EMC	Safety Standards	EN61347-1, EN61347-2-13
	Withstand Voltage	I/P-O/P: 3.75KVAC
	Isolation Resistance	I/P-O/P: 100M Ohms / 500VDC / 25°C / 70% RH
	EMC Emission	En55015, EN61000-3-2, EN61000-3-3
Others	EMC Immunity	En61547, EN61000-4-2,3,4,5,6,8,11
	MTBF	191350H, MIL-HDBK-217F @ 230VAC full load and 25°C ambient temperature
	Dimension	280x30x21mm (L*W*H)
	Warranty	5 Years

- In compliance with IEC 62386-101:2014, IEC 62386-102:2014, IEC 62386-207 Ed2,
- Built-in DALI-2 interface, DALI DT6 device
- Dimmable LED driver with linear metal housing. Max. output power 60W
- 900-1700mA current selectable via NFC program tool. Min. current gear lower to 0.1mA
- DALI Address/Group/Scene setting via NFC program tool.
- Class II power supply, isolated design
- High power factor and efficiency
- To switch and dim LED lighting luminaries
- Amplitude/CCR dimming, smooth and deep dimming
- Compatible with universal DALI masters that support DT6 commands
- DALI-250/251/252/253 Enabled, DALI data inside.
- Integrated Max.56mA DALI BUS supplu, enabled to powered DALI-2 sensors.
- IP20 rating, suitable for indoor LED lighting applications
- 5 years warranty

Safety & Warnings

- DO NOT install with power applied to the device.
- DO NOT expose the device to moisture.

Operation

With DALI master

1. DALI Address

1 DALI address for 1 channel output are assigned by DALI Master controller automatically, please refer to user manuals of compatible DALI Masters for specific operations.

With NFC Programming devices

Note

1) Do wiring according to the wiring diagram and power on the DALI system .

2) Recommend setting parameters without power-on the DALI devices .

2) Please make sure your mobile phone has NFC function and enable it .

Working with “SR NFC Tool” APP


Step 1: Download the APP (searching “SR NFC Tool” from App Store and Google Play) .
Then open the APP .




Download
“SR NFC
Tool”

- Note:**
1. Please Make sure that you have enabled NFC function with your mobile phone/ tablet .
 2. Please Make sure that the “NFC position” is matched.
 3. Please do not power on the device before setting.
 4. If you can't download “SR NFC Tool”. Please contact with us.

Step 2: Add device, and name it as you wish.




Step 3: Unlock device, enter parameters configuring page.



- Note:**
1. You have to unlock the device then do some settings
 2. Only when the corresponding function is selected, the function interface will be displayed.

Step 4: Few parameter interface, you can choose the setting based on your requirements.




Step 5: After setting, please save the selected configuration via NFC and power on the device.



Tips

1. NFC function doesn't require any power driver.
2. Many functions can be configured by NFC. Kindly check your desired functions.
3. All of our DALI drivers are in the best performance within our DALI master/ gateway.

2. Enter CLO Setting homepage



Enable CLO function

Click "1", and set its time and level


Set your desired time and levels.
Graphic display

Tips:

Working hours : Ability to calculate the working hours of a single driver.

CLO AND CORRIDOR DIM(CD) FUNCTION INSTRUCTION

1. Open APP, and Find the CLO/CD functions




Read From the NFC Driver

Unlock it, and Click here to enter CLO settings

Enable or Disable CLO function

3. Corridor dim(CD) function



Read From the NFC Driver

Unlock it, and Click here to enter Corridor mode

Mode

CD PD

PD: PUSH DIM

CD: Corridor DIM

4. Enter CD Setting homepage

Cancel Corridor Save

Mode

CD PD

Preview

Level (%)

Fade in Occupied Fade out Prolonged Dim to off

Fade in time

5 s

Value range 0-100

Occupied time

120 s

Value range 0-60,000

Occupied level

100 %

Value range 0-100

Fade out time

5 s

Value range 0-100

Prolonged time

60 s

Value range 0-60,000

Occupied level

Infinite

Prolonged level

20 %

Value range 0-100

Dim to off time

5 s

Value range 0-100

Read Write

Enter CD mode

Tips:

1. You should select either CD mode or PD mode, but not both.
2. Under CD mode, you can realize it with normal (3rd party) AC sensor.
3. Default mode: PD mode.

Additional Remarks

More

Write Consecutively

Advanced >

App Version 1.0.10


Check for Update >

Privacy Policy >

Configurations More

1. Please make sure your APP version is 1.0.10 or higher.
2. Please make sure NFC driver's firmware is available with CLO / CD functions.

Product Dimension




Wiring Diagram

1. As a D4i Driver




2. As a Normal DALI driver.

2.1 With DALI bus




2.2 With PUSH dimmer




AC Push Function

- 1) Click the button to switch ON/OFF
- 2) Press and hold down the button to increase or decrease light intensity to desired level and release it, then repeat the operation to adjust light intensity to opposite direction. The dimming range is from 1% to 100%.


Operating window




Dimming Curve




Driver Performance



Driver Performance



Driver Performance




Expected Lifetime

Module Number	Output current	Ta	30 °C	40 °C	45 °C	•••	60 °C
SRPL-2305iN-60CC900-1700	900 – 1700 mA	Tc	52 °C	62 °C	66 °C	•••	90 °C(max)
SRPL-2309iN-60CCT900-1700	900 – 1700 mA	Lifetime	> 100,000 h	> 80,000 h	> 60,000 h		> 25,000 h

The LED driver is designed for a lifetime stated above under reference conditions .
The relation of tc to ta temperature depends also on the luminaire design.

MCB Load Quantity

Module Number	I _{peak}	T _{width}	Max. quantity of LED Driver per MCB														
			B10	B13	B16	B20	B25	C10	C13	C16	C20	C25	D10	D13	D16	D20	D25
SRPL-2305iN-60CC900-1700	25.9A	148μs	15	20	24	30	38	18	23	28	35	44	20	26	32	40	50
SRPL-2309iN-60CCT900-1700	25.9A	148μs	15	20	24	30	38	18	23	28	35	44	20	26	32	40	50



Note:

1. Those MCB parameters are based on ABB S200 series circuit breakers.
2. For different brands and models of miniature circuit breakers, the quantity of drivers will have difference.
3. Please do not exceed the above-mentioned quantity during on-site installation, and the specific load quantity shall be subject to on-site installation.
4. When the installation environment temperature of MCBs exceeds 30°C or when multiple MCBs are installed side by side, the number of mounted drives will be reduced, which requires recalculation.
5. Type C MCB's are strongly recommended to use with LED lighting

Update log

Date	Version	Update content	Update by
2023-9-1	V1.5	Parameter Update	Romeo

Note: Subject to change without notice. Please contact us if you have any questions.